



NOTE: MAGNET SHOULD BE INSTALLED BETWEEN IDLERS. ANY IDLERS DIRECTLY BENEATH THE MAGNET SHOULD BE OF NON-MAGNETIC MATERIAL.

TYPE	A	B	C	D	E	F	MOTOR	WEIGHT
14 PCB 6	2800	1450	800	800	900	950	3.0 KW	2410
14 PCB 7	2950	1525	875	875	1000	1100	3.0 KW	2695
14 PCB 8	3100	1600	950	950	1200	1250	3.0 KW	2965
14 PCB 9	3250	1675	1025	1025	1400	1400	3.0 KW	3235
14 PCB 10	3400	1750	1100	1100	1500	1560	3.0 KW	3505

E	REDRAWN ON C.A.D	DF	05/00
MOD	DESCRIPTION	SIGN	DATE
THIS DRAWING AND INFORMATION IS THE PROPERTY OF KW SUPPLY MAGNET SYSTEMS, AND MUST NOT BE COPIED OR RELATED TO A THIRD PARTY WITHOUT WRITTEN PERMISSION.			

**KW SUPPLY**  
**MAGNET SYSTEMS**  
 ROTTERDAM  
 HOLLAND  
 TEL: +31(0)10-4291380  
 FAX: +31(0)10-4292168  
 WWW.KWSUPPLY.COM

SIGN	DATE
DRAWN DF	05/00
CHECKED	
APPROVED	
SCALE	1:20

**KW Supply**  
**magnet systems**

TITLE	OUTLINE DIMENSIONS FOR 'KW SUPPLY' TYPE 14 P.C.B K PERMANENT OVERBAND SEPARATORS
PROJECTION	
A3	4066
ISSUE	E